

# Call Number Hierarchies

**Scope:** Call number hierarchies tell the Voyager system where in a bibliographic record to find call number information. That information will be taken from the fields outlined in the call number hierarchy and be placed in field 852, subfields h and i of the MFHD when a new MFHD is created. Call number hierarchies are set in System Administration.

**Contact:** [Gary Branch](#)

**Date last modified:** 10/04/18

---

## Library of Congress

To define the Library of Congress call number hierarchy, do the following:

- In System Administration, go to **Cat**, then click the **Call Number Hierarchy** button.
- Click the **Add Hierarchy** tab on the right. In the **Hierarchy Name** field, type **Library of Congress**. In the code field, type **LC**. Check the **Use as default** tab, and in the **Call Number Type** pull-down list, select **Library of Congress**.
- Click on the **Call Number** tab, then the **add** button on the right. Define the hierarchy as follows by adding the following fields, indicators, and subfields:

Indicator 1	Indicator 2	Field	Main subfield	Cutter subfield
*	0	050	a	b
*	(blank)	050	a	b
*	4	050	a	b
(blank)	(blank)	090	a	b
(blank)	(blank)	090	a	
(blank)	(blank)	950	a	b

---

## Mapped (LC)

Used for bulk import of records in which an LC call number is found in an 050 or 090 field using the location present in 952 subfield b.

- Hierarchy Name = Mapped (LC)
- Code = MAPPEDLC
- Call Number Type = Library of Congress

Indicator 1	Indicator 2	Field	Main subfield
*	*	952	b

---

## Mapped (Non-LC)

Used for bulk import of records in which a non-LC call number has been mapped into a BIB 952 field, but can use an 852 field (Shelf ready, for example) to create exact duplicate on new MFHD during bulk import.:

- Hierarchy Name = Mapped (Non-LC)
- Code = MAPPED
- Call Number Type = Other

Indicator 1	Indicator 2	Field	Main subfield	Cutter subfield	Oversize or collection text	Oversize symbol or collection text	Public note	Non-public note
*	*	952	h	i				
*	*	852	h	i	k	m	z	x

---

### Mapped (Recon)

Used for bulk import of records in which a non-LC call number has been mapped into a BIB 947 field:

- Hierarchy Name = Mapped (Recon)
- Code = MAPPEDRE
- Call Number Type = Other

Indicator 1	Indicator 2	Field	Main subfield	Cutter subfield
*	*	947	a	b

*Note: This hierarchy was formerly used for LC call numbers. It was changed after the completion of LC-class recon.*